


Podwójna dioda


6V4

Pr prostownik pełnookresowy

Nowal



$U_z = 6.3 V$
 $I_z = 0.6 V$



Wartości maksymalne

| | | | | |
|---------------|----------------|----------------|----------------|----------|
| U_{trmax} | 2×220 | 2×250 | 2×350 | V |
| $I_{=max}$ | 90 | 90 | 90 | mA |
| $U_{=max}$ | 230 | 265 | 360 | V |
| R | 2×75 | 2×125 | 2×300 | Ω |
| C_L | 50 | 50 | 50 | μF |
| $U_{wlkszcz}$ | | 500 | — | V |

TYPY PODOBNE

EZ 80