



T.			$U_f$	$I_f$	$U_{tr(C)}$	$U_{tr(L)}$	$U_p$	$I_o$	$I_p$	$R_{tr}$	$L_F$	$C_F$
			V	A	V	V	V	mA	mA	$\Omega$	H	$\mu F$
5 AZ 4	amer	1	5	2	350	500	1400	125	375	50	10	
5 Y 3-G	int	2	5	2								
5 Y 3-WGT <sup>1)</sup>	amer	2	5±10%	2								
5 Y 4-G	amer	3	5	2								
5 Z 4	int	4	5	2								
80	int	5	5	2								
80 S	int	6	5	3								
6004	amer	7	5	2								
6106 <sup>2)</sup>	amer	2	5±5%	2								
5 Y 3-GB	Maz	4	5	1,7	{ 400	550	110		10	20	4	
					{ 350		135					
5 Y 3-GR	Fiv	2	5	1	{ 350	500	1400	100	300	5	8	
5 II 4 M	CCCP	4	5±10%	2	400	1650	1550	135	415			4
Г P 1-0,25/1,5	CCCP	6	5±10%	3	500		125	800	8			

<sup>1)</sup> vide \*4, a, b, d, g

<sup>2)</sup> vide \*4, a, b, c, d, g

### Equivalents

BГ 0,25/1500	CCCP = ГП1-0,25/1,5	5 BX 2	CCCP = 5 Y 3-G	88	amer = 80
BГ 8	CCCP = ГП1-0,25/1,5	5 Y 3 C	CCCP = 5 Y 3-G	113	amer = 80
CX 313	amer = 5 Y 3-G	5 Y 3-GA	amer = 5 Y 3-G	113 B	amer = 80
D 1	amer = 5 Y 3-G	5 Y 3-GT	int = 5 Y 3-G	180	amer = 80
EX 680	amer = 80	<b>5 Y 3-WGTA<sup>1)</sup></b>	amer = 5 Y 3-WGT	213	amer = 80
G 80	amer = 80	<b>5 Y 3-WGTB<sup>1)</sup></b>	amer = 5 Y 3-WGT	213 B	amer = 80
GZ 30	Mul = 5 Z 4	5 Y 4-GA	amer = 5 Y 4-G	268	amer = 80 S
ГA 0,25/1,5	CCCP = ГП1-0,25/1,5	5 Y 4-GT	int = 5 Y 4-G	280	amer = 80
OSW 3107	RFT = 5 Z 4	5 Y 4-SG	Syl = 5 Z 4	280 M	amer = 80 S
R 52	Fer = 5 Y 3-G	5 Z 4 C	RFT = 5 Z 4	288	amer = 80 S
R 80	amer = 80	5 Z 4-G	int = 5 Z 4	313	amer = 80
RE 1	amer = 5 Y 3-G	5 Z 4-MG	int = 5 Z 4	313 B	amer = 80
T 80	amer = 80	5 Z 5-MG	int = 5 Z 4	380	amer = 80
UX 213	amer = 80	5 II 4 C	CCCP = 5 Z 4	480	amer = 80
UX 280	amer = 80	13	amer = 5 Y 3-G	580	amer = 80
UX 380	amer = 80	13 B	amer = 80	583	amer = 80
WT-270	amer = 80	80/41	amer = 80	2800	amer = 80
WTT-102	amer = 5 Y 3-GT	80 A	amer = 80	<b>6087</b>	amer = 5 Y 3-G
XV 280	amer = 80	80 M	amer = 80	38080	amer = 80
5 BX 1	CCCP = 5 Z 4				

